
90X5W LED ZOOM MOVING WASH

USER MANUAL

Ver1.0

Table of contents

1. Preface	2
1.1 Packing list	2
1.2 Unpacking instructions	2
1.3 AC Power	2
1.4 Safety instructions	2
2. Introduction	3
2.1 Features	3
2.2 DMX channel	3
3. Setup	3
3.1 Fuse replacement	4
3.2 Fixture linking	4
Data cabling	4
DMX data cable	4
3.3 3-Pin to 5-Pin conversion chart	4
3.4 Setting up a DMX serial data link	4
3.5 Master/Slave fixture linking	4
3.6 orientation	5
4. Operating instructions	5
4.1 Navigating the control panel	5
4.2 Menu map	5
DMX mode	5
4.3 DMX channel values	6
5. Technical specifications	7

1. Preface

1.1 Packing list

Product name	quantity
moving head light	1 pcs
Power -line	1 base
User manual	1pcs

1.2 Unpacking instructions

On receiving a fixture, carefully unpack the carton, check the contents to ensure that all parts are presented, and have been received in a good condition. Notify the shipper immediately and retain packing material for inspection if any parts appear damaged from shipping or the carton itself shows, sign of mishandling. Save the carton and all packing materials. In the event that a fixture must be returned to the factory, it is important that the fixture should be returned in original factory box and packing.

1.3 AC Power

To determine the power requirements for a particular fixture, see the label affixed to the back plate of the fixture or referred to the fixtures specification chart. A fixture listed current rating is its average current draw under normal conditions. All fixtures must be directly powered off a switched circuit and cannot be run off a rheostat (variable resistor) or dimmer circuit, even if the rheostat or dimmer source voltage matches the fixtures requirement. Check the fixture or device carefully to make sure that if a voltage selection switch exists that it is set to the correct line voltage you will use.

Warning! Verify that the voltage select switch on your unit matches the line voltage applied. Damage to your fixture may result if the line voltage applied does not match the voltage indicated on the voltage selector switch. All fixtures must be connected to circuits with a suitable Earth ground.

1.4 Safety instructions

Please read these instructions CY, it includes important information about the installation, usage and maintenance of this product.

Please keep this user guide for future consultation. If you sell the unit to another user, be sure that they also receive this instruction booklet.

Always make sure that you are connecting to the proper voltage, and that the line voltage you are connecting to is not higher than that stated on the decal or rear panel of the fixture.

This product is intended for indoor use only!

To prevent risk of fire or shock, do not expose fixture to rain or moisture. Make sure that there are no flammable materials close to the unit while operating.

The unit must be installed in a location with adequate ventilation, at least 20in (50cm) from adjacent surfaces. Be sure that no ventilation slots are blocked.

Always disconnect from power source before servicing or replacing fuse and be

sure to replace with same fuse size and type.

Secure fixture to fastening device using a safety chain. Never carry the fixture solely by its head. Use its carrying handles.

Maximum ambient temperature (Ta) is 104 °F (40 °C). Do not operate fixture at temperatures higher than this.

In the event of a serious operating problem, stop using the unit immediately. Never try to repair the unit by yourself. Repairs carried out by unskilled people can lead to damage or malfunction. Please contact the nearest authorized technical assistance center. Always use the same type spare parts.

Don't connect the device to a dimmer device.

Make sure the power cord never crimped or damaged.

Never disconnect the power cord by pulling or gugging on the cord.

Avoid direct eye exposing to the light source while it is on.

2. Introduction

2.1 Features

16 channel DMX-512 .in optional

Pan :540° /tilt:270° .

Variable electronic strobe.

Variable electronic dimmer (0-100%).

LCD display

Reset to factory settings option.

Pan/tilt inverts option.

Fan cooled.

2.2 DMX channel

Channel	Function
1	Dimmer
2	Red
3	Green
4	Blue
5	White
6	Strobe
7	Color change
8	Mixed Color
9	Auto mixed color
10	Pan
11	Tilt
12	Pan Fine
13	Tilt Fine
14	Pan/Tilt Speed
15	Reset
16	Zoom

3. Setup

Disconnect the power cord before replacing a fuse and always replace with the same type fuse.

3.1 Fuse replacement

With a flat head screwdriver wedge the fuse hold out of its housing. Remove the damaged fuse from its holder and replace with exact same type fuse. Insert the fuse holder back in its place and reconnect power.

3.2 Fixture linking

You will need a serial data link to run light show of one or more fixtures using a DMX-512 controller or to run synchronized on two or more fixtures set to a master/slave operating mode. The combined number of channels required by all the fixtures on a serial data link determines the number of fixtures the data link can support.

Maximum recommended serial data link distance: 500 meters (1640ft).

Maximum recommended number of fixtures on a serial data link: 32 fixtures.

Data cabling

To link fixtures together you must obtain data cables. If you choose to create your own cable please use data-grade cables that can carry a high quality signal and are less prone to electromagnetic interference.

DMX data cable

Use a belden 9841 or equivalent cable which meets the specifications for EIA RS-485 applications. Standard microphone cables cannot transmit DMX data reliably over long distances. The cable will have the following characteristics:

2-conductor twisted pair plus a shield.

Maximum capacitance between conductors-30 pF/ft.

Maximum capacitance between conductor and shield -55 pF/ft.

Maximum resistance of 20 ohms/1000ft.

Nominal impedance 100-140 ohms.

3.3 3-Pin to 5-Pin conversion chart


Note! If you use a controller with a 5 pin DMX output connector. You will need to use a 5pin to 3 pin as apter

CHAUVET Model No: DMX5M. Or DMX 5F

The chart below details a proper cable conversion:


Occupation of the XLR-connection:

DMX - output
XLR mounting-sockets (rear view):



- 1 - Shield
- 2 - Signal (-)
- 3 - Signal (+)
- 4 - Not connected
- 5 - Not connected

DMX-input
XLR mounting-plugs (rear view):



3.4 Setting up a DMX serial data link

3.5 Master/Slave fixture linking

1. Connect the (male) 3 pin connector side of the DMX cable to the output (female) 3pin connector of the first fixture.

2. Connect the end of the cable coming from the first fixture which will have a (female) 3 pin connector to the input connector of the next fixture consisting of a (male) 3 pin connector. Then, proceed to connect from the output as stated above to the input of the following fixture and so on.

3.6 orientations

This fixture may be mounted in any position provided there is adequate room for ventilation.

4. Operating instructions

4.1 Navigating the control panel

Access control panel functions using the four panel buttons located directly underneath the LCD Display.

Button	Function
<MENU>	Used to access the menu or return to a previous menu option.
<DOWN>	Scrolls through menu options in descending order.
<UP>	Scrolls through menu options in ascending order.
<ENTER>	Used to select and store the current menu or option within a menu.

When a menu function is selected, the display will show immediately the first available option for the selected menu function. To select a menu item, press<ENTER>.

Press the <MENU> button repeatedly until you reach the desired menu function. Use the <UP> and <DOWN> buttons to navigate the menu options. Press the <ENTER> button to select the menu function currently displayed, or to enable a menu option. To return to the previous option or menu without changing the value, press the <MENU> button.

No alternative worth that return re-option or menu, press (MENU) button

4.2 Menu map

DMX Address (DMX address 001-512)

Perform mode (Quick or Slow)

Sound Control (000 sound color or 001 sound strobe)

Pan Reverse (000 Pan or 001 Pan reverse)

Tilt Reverse (000 Pan or 001 Pan reverse)

Factory Set (setting 001 for factory setting)

Reset Set (setting 001 for reset)

Note:

1. Confirm the factory set or change the pan angle that will cause system reset, this is for reconfirm the starting point and the terminal point of the pan movement.
2. The pan movement is 540° and the different in pan position is 180° between

with pan and pan reverse, the pan movement is 630 ° , the different in pan position is 90 ° between with pan and pan reverse.

DMX mode

This mode allows the until to be controlled by any universal DMX controller.

The default mode for the fixture is DMX, as follow.

Choose the device which is to control the effect. This device then works as master-device and controls all other slave-device, which are to be connected to the master-device via a balanced microphone lead.

Set the desired Master-mode- “Automatic Program mode” or “Sound Controlled mode”,- for the master-device.

Master/slave mode(auto-running、 sound control)

.This mode will allow you to link up 32 units together without a controller.

.Use standard DMX cables to daisy chain your units together via the DMX connector on the rear of the units. Proper performance it may be necessary to use a terminator at the last fixture. For more information about terminators...

Master: choose auto or sound control mode

Slave: choose DMX mode and the address code must be 001

4.3 DMX channel values

Channel	Value	Function
1	0-255	Dimmer 0-100% dimmer
2	0-255	Red 0-100% Red
3	0-255	Green 0-100% Green
4	0-255	Blue 0-100% Blue
5	0-255	White 0-100% White
6	0-255	Strobe Strobe effect
7	0-15 16-31 32-47 48-63 64-79 80-95 96-111 112-127 128-143 144-159 160-175 176-191 192-207	Color Change No function Red Green Blue White Red/Green Red/Blue Red/White Green/Blue Green/White Blue/White Red/Green/Blue Red/Green/White

	208-223 224-239 240-255	Green/Blue/White Blue/Red/White Red/Green/Blue/White
8	0-2 3-41 42-83 84-125 126-167 168-209 210-251 252-255	Mixed color No function R: 100% B: 0 G:0~100% R: 100%~0 B: 0 G:100% R: 0 B:0~100% G:100% R: 0 B:100% G:100%~0 R: 0~100% B: 100% G: 0 R:100% B:100% G:0~100% R:100% B:100% G:100%
9	0-2 3-255	Auto Mixed color No function Auto Mixed color with increasing speed
10	0-255	Pan Pan movement 0~540
11	0-255	Tilt Tilt movement 0~270
12	0-255	Pan Fine Pan fine
13	0-255	Tilt Fine Pan fine
14	0-255	Pan Tilt speed Pan & Tilt speed adjustment
15	0-127 128-255	Reset No function Reset after 3 seconds
16	0-255	Zoom From narrow to wide

5. techno-specification illuminates

Voltage	AC100/240v 60/50Hz
LEDs	90*5w RGBW LEDs
Pan	540°
Tilt	270°
Tiptop environment temperature	104°F(40°C)
Date input/output	3pin XLR-connection、 anode socket
Outside size	210 ×300×430mm(L×W×H)
N.W	10.2kg
Packing size	400×320×460mm(L×W×H)(1pcs/package)
G.W	11.35kg